

VTi® CELTIC RECHARGEABLE BATTERY MOTOR | 3 Nm 6-700-CM-35EB3



FEATURES

- Internal rechargeable lithium battery, that lasts about half a year under normal operation (one cycle per day).
- Wirefree: Does not require electrical wiring, no external battery pack and no complicated installation.
- Recommended for shades with dimensions up to 140" x 120" | 3.5 m x 3.0 m.
- Operation as quiet as 40 dB.
- Simple electronic setting of limits and other adjustments.
- Up to 4 intermediate limits can be preset.
- Jogging function for Neolux® and tilting for Horizontal Blinds.
- The motor emits a notification sound when the battery charge reaches 10%.
- Smart control with VTi® Smart Hub, anytime, anywhere.
- Compatible with leading brands of Home Automation Systems.

APPLICATIONS





Roller Shades

Neolux Dual Shades



Horizontal Blinds

CONTROL SOLUTIONS



Neo RF Emitter 1, 6 & 16 Channels



Wave RF Emitter 2 & 6 Channels



VTi® Celtic RF Wireless Pick Up Wall Switch 2 & 6 Channels



VTi® Celtic RF Wireless Wall Switch 1 & 6 Channels



Timer Touch & Wall Switch 16 Channels

SMART SOLUTIONS



VTi® Celtic Serial Interface



Smart Hub



VTi HomeMate App

CERTIFICATIONS










VTi® CELTIC RECHARGEABLE BATTERY MOTOR | 3 Nm 6-700-CM-35EB3

DIMENSIONS



^{*}All measurements are reflected in millimeters.

TECHNICAL SPECS

| Torque | 3 Nm | Current | 3.0 A |
|------------------|------------|--------------------|-----------------------------|
| Speed | 28 rpm | Thermal Protection | 5 Minutes |
| Sound Level | 40 dB | Voltage Supply | 12 V DC |
| Limits | Electronic | Radio Frequency | 433.92 MHz |
| Index Protection | IP 44 | Maximum Shade Size | 140" x 120" 3.5 m x 3.0 m |
| Power | 36 W | Weight Capacity* | 24 lb 10.8 kg |

^{*}The maximum weight capacity is calculated under optimal circumstances. Actual results may vary. Specifications are subject to change without notice.

CHARGING SOLUTIONS



Li-ion Battery Charger 16.8 V DC | 1.5 A 6-700-CM-DC002

RECOMMENDED TUBES



^{*}Find all recommended tubes, along with their crowns, drives & end plug adapters in the Compatible Tubes & Adapters Section, at the end of this Manual.
**These tubes require a notch on the crown adapter or counter ring and 2 rivets on the drive in order to avoid slipping.

60